LIST OF MATERIALS & INPUT FILE
TRAFFIC SIGNAL INSTALLATION NO. 6

LIST OF MATERIALS	UNIT	QUANTITY
CONTROLLER CABINET ASSEMBLIES		
A. CONTROLLER UNIT, MODEL 2070L	EA	1
D. CABINET ASSEMBLY, MODEL 332A	EA	1
E. SWITCH PACK	EA	8
F. DC ISOLATOR	EA	3
G. LOOP DETECTOR, 2 CHANNEL	EA	4
J. 2010 CONFLICT MONITOR, EXTENDED FEATURES	EA	1
332A PREFABRICATED CONTROLLER CABINET BASE	EA	1
LOOP/PED LEAD-IN WIRE (SHIELDED, TWISTED/1000 FT)		
A. 3 PAIR, 18 AWG	REEL	2
SIGNAL CABLE (14 AWG)		
B. 7 CONDUCTOR, PER 1000 FT.	REEL	2
LOOP DETECTOR WIRE (14 AWG, STRANDED/1000 FT)	REEL	1
ONE-WAY, 3-SECTION, 12" SIGNAL HEAD w/(5mm) PIXELATED VIEW LED's, PLASTIC	EA	8
ONE-WAY, 1-SECTION, 18" LED COUNTDOWN PEDESTRIAN SIGNAL HEAD, FULL HAND/MAN OVERLAP		
1. 9" HIGH, Numbers	EA	8
PEDESTRIAN PUSH STATION ASSEMBLY		
B. 9" x 15", w/Double Push Button Station Adapter for 4" Dia Pedestrian Pole, Adjustable	EA	8
PEDESTRIAN PUSHBUTTONS STATIONS, w/BUTTONS and SIGNS:		
B. 9" x 15", R10-3e, (L)eft or (R)ight, Countdown	EA	8
BACK PLATE FOR ONE-WAY, 3-SECTION, 12" SIGNAL HEAD	EA	8
HARDWARE FOR MAST ARM MOUNTING	EA	8
HARDWARE FOR PEDESTAL POLE, TOP POST MOUNTING, TWO-WAY BRACKET ASSEMBLY	EA	3
HARDWARE FOR SIDE-OF-POLE MOUNTING, TWO-WAY BRACKET ASSEMBLY	EA	1
PEDESTAL POLE & SQUARE BASE	EA	3
LOOP SAW CUT	LF	504
MISCELLANEOUS MATERIALS NEEDED TO COMPLETE INSTALLATION	LUMP	LUMP

332 CABINET INPUT ASSIGNMENT

SLOT	1	2	3	4	5	6	7	8	9	10	11	12	13	14

UPPER INPUT FILE

	TYPE		DET				DET				TBA	TBA	DC	DC	DC
	CARD		2 CHAN				2 CHAN						DC ISO	DC ISO	DC ISO
CHANNEL 1	CI PIN	56	39	63	47	58	41	65	49	60		80	67	68	81
	FUNCTION		L2				L4						Ø2 PED	Ø6 PED	FLASH
	FIELD TERM	TB2 1,2	TB2 5,6	TB2 9,10	TB4 1,2	TB4 5,6	TB4 9,10	TB6 1,2	TB6 5,6	TB6 9,10			TB8 4,6	TB8 7,9	N/C
CHANNEL 2	CI PIN	56	43	76	47	58	45	78	49	62		53	69	70	82
	FUNCTION												Ø4 PED	Ø8 PED	STOP TIME
	FIELD TERM	TB2 3,4	TB2 7,8	TB2 11,12	TB4 3,4	TB4 7,8	TB4 11,12	TB6 3,4	TB6 7,8	TB6 11,12			TB8 5,6	TB8 8,9	N/C

LOWER INPUT FILE

	TYPE		DET				DET				TBA	TBA	DC	DC	DC
	CARD		2 CHAN				2 CHAN								
CHANNEL 1	CI PIN	55	40	64	48	57	42	66	50	59		54	71	72	51
	FUNCTION		L6				L8								
	FIELD TERM	TB3 1,2	TB3 5,6	TB3 9,10	TB5 1,2	TB5 5,6	TB5 9,10	TB7 1,2	TB7 5,6	TB7 9,10			TB9 4,6	TB9 7,9	TB9 10,12
CHANNEL 2	CI PIN	55	44	77	48	57	46	79	50	61		75	73	74	52
	FUNCTION														
	FIELD TERM	TB3 3,4	TB3 7,8	TB3 11,12	TB5 3,4	TB5 7,8	TB5 11,12	TB7 3,4	TB7 7,8	TB7 11,12			TB9 5,6	TB9 8,9	TB9 11,12